



Minimum fuse size for the protection of three-phase motors

The maximum size is governed by the requirements of the associated switchgear or overload relay

MOTOR RATING			230V			400V			500V			690V		
kW	cos	η(%)	Rated Motor Current	Fuse Starting Direct	Y/	Rated Motor Current	Fuse Starting Direct	Y/	Rated Motor Current	Fuse Starting Direct	Y/	Rated Motor Current	Fuse Starting Direct	Y/
			A	A	A	A	A	A	A	A	A	A	A	A
0.06	0.7	58	0.37	2	-	0.21	2	-	0.17	2	-	0.12	2	-
0.09	0.7	60	0.54	2	-	0.31	2	-	0.25	2	-	0.18	2	-
0.12	0.7	60	0.72	4	2	0.41	2	-	0.33	2	-	0.24	2	-
0.18	0.7	62	1.04	4	2	0.6	2	-	0.48	2	-	0.35	2	-
0.25	0.7	62	1.4	4	2	0.8	4	2	0.7	2	-	0.5	2	-
0.37	0.72	66	2	6	4	1.1	4	2	0.9	2	2	0.7	2	-
0.55	0.75	69	2.7	10	4	1.5	4	2	1.2	4	2	0.9	4	2
0.75	0.79	74	3.2	10	4	1.9	6	4	1.5	4	2	1.1	4	2
1.1	0.81	74	4.6	10	6	2.6	6	4	2.1	6	4	1.5	4	2
1.5	0.81	74	6.3	16	10	3.6	6	4	2.9	6	4	2.1	6	4
2.2	0.81	78	8.7	20	10	5	10	6	4	10	4	2.9	10	4
3	0.82	80	11.5	25	16	6.6	16	10	5.3	16	6	3.8	10	4
4	0.82	83	14.8	32	16	8.5	20	10	6.8	16	10	4.9	16	6
5.5	0.82	86	19.6	32	25	11.3	25	16	9	20	16	6.5	16	10
7.5	0.82	87	26.4	50	32	15.2	32	16	12.1	25	16	8.8	20	10
11	0.84	87	38	80	40	21.7	40	25	17.4	32	20	12.6	25	16
15	0.84	88	51	100	63	29.3	63	32	23.4	50	25	17	32	20
18.5	0.84	88	63	125	80	36	63	40	28.9	50	32	20.9	32	25
22	0.84	92	71	125	80	41	80	50	33	63	32	23.8	50	25
30	0.85	92	96	200	100	55	100	63	44	80	50	32	63	32
37	0.86	92	117	200	125	68	125	80	54	100	63	39	80	50
45	0.86	93	141	250	160	81	160	100	65	125	80	47	80	63
55	0.86	93	173	250	200	99	200	125	79	160	80	58	100	63
75	0.86	94	233	315	250	134	200	160	107	200	125	78	160	100
90	0.86	94	279	400	315	161	250	200	129	200	160	93	160	100
110	0.86	94	342	500	400	196	315	200	157	250	160	114	200	125
132	0.87	95	401	630	500	231	400	250	184	250	200	134	250	160
160	0.87	95	486	630	630	279	400	315	224	315	250	162	250	200
200	0.87	95	607	800	630	349	500	400	279	400	315	202	315	250
250	0.87	95	-	-	-	437	630	500	349	500	400	253	400	315
315	0.87	96	-	-	-	544	800	630	436	630	500	316	500	400
400	0.88	96	-	-	-	683	1000	800	547	800	630	396	630	400
450	0.88	96	-	-	-	769	1000	800	615	800	630	446	630	630
500	0.88	97	-	-	-	-	-	-	-	-	-	491	630	630
560	0.88	97	-	-	-	-	-	-	-	-	-	550	800	630
630	0.88	97	-	-	-	-	-	-	-	-	-	618	800	630

Notes:

The rated motor currents apply to normal, internally-ventilated and enclosed fan-cooled three-phase motors at 1500 -1rpm.

DOL starting: Maximum starting current 6 × rated motor current.

Y/ starting: Maximum starting current 2 × rated motor current.

Maximum starting time 5 seconds
Maximum starting time 15 seconds
Set the overload relay in the phase lead to 0.58 × rated motor current.

Rated fuse currents for Y/ starting also apply to the three-phase motors with slip-ring rotors.

Use a larger fuse if the rated current or starting current is higher and /or if the starting time is longer.
The table applies to "slow" and "gl" fuses (VDE 0636)

LV h.b.c. fuses with aM characteristics, select fuse size to match rated current.

Data Courtesy Of:



Leeds

Tel: 0113 243 0203

Sheffield

Tel: 0114 243 1841

Gateshead

Tel: 0191 460 2233

Manchester

Tel: 0161 876 4337

Glasgow

Tel: 0141 892 0166

Walsall

Tel: 01922 724604

e-mail: sales@scatts.co.uk

web: www.scatts.co.uk