

CONTACTRON modules



CONTACTRON modules detect and signal an under-range in the current measuring range

Application note
105461_en_00

© PHOENIX CONTACT 2012-11-27

1 When the message appears

The message appears in the following cases, when there is a pending control signal:

- The motor current is below the lowest possible current setting
- The two-phase current is below the minimum possible current setting
- No motor connected
- No mains voltage due to missing or triggered mains fuse

Current product version			LED error message	Feed-back relay	Power path switch-off
L1	L2	L3			
$I_N \geq I_{min}$	$I_N \geq I_{min}$	$I_N \geq I_{min}$	-	-	-
$I_N < I_{min}$	$I_N < I_{min}$	$I_N < I_{min}$	-	-	-
$I_N < I_{min}$	$I_N < I_{min}$	$I_N \geq I_{min}$	-	-	-
$I_N < I_{min}$	$I_N \geq I_{min}$	$I_N < I_{min}$	-	-	-
$I_N \geq I_{min}$	$I_N < I_{min}$	$I_N < I_{min}$	-	-	-
$I_N \geq I_{min}$	$I_N \geq I_{min}$	$I_N < I_{min}$	x	x	x
$I_N < I_{min}$	$I_N \geq I_{min}$	$I_N \geq I_{min}$	x	x	x
$I_N \geq I_{min}$	$I_N < I_{min}$	$I_N \geq I_{min}$	x	x	x

New product version (see section 7)			LED error message	Feed-back relay	Power path switch-off
L1	L2	L3			
$I_N \geq I_{min}$	$I_N \geq I_{min}$	$I_N \geq I_{min}$	-	-	-
$I_N < I_{min}$	$I_N < I_{min}$	$I_N < I_{min}$	x	x	-
$I_N < I_{min}$	$I_N < I_{min}$	$I_N \geq I_{min}$	x	x	-
$I_N < I_{min}$	$I_N \geq I_{min}$	$I_N < I_{min}$	x	x	-
$I_N \geq I_{min}$	$I_N < I_{min}$	$I_N < I_{min}$	x	x	-
$I_N \geq I_{min}$	$I_N \geq I_{min}$	$I_N < I_{min}$	x	x	x
$I_N < I_{min}$	$I_N \geq I_{min}$	$I_N \geq I_{min}$	x	x	x
$I_N \geq I_{min}$	$I_N < I_{min}$	$I_N \geq I_{min}$	x	x	x

I_N = motor current, I_{min} = minimum current that can be set for motor protection

2 What does this message mean for the application?

The measuring system is not active, no motor protection is in place, safe switch-off is not guaranteed.

3 Advantages

If no message occurs during control, the motor is running.



Make sure you always use the latest documentation. It can be downloaded at www.phoenixcontact.net/products



This document is valid for all products listed on the following page:

4 Specified current ranges

It is important to take note of the following current ranges for the different CONTACTRON modules with regard to the nominal motor current:

- 0.6 A modules: 0.075 A ... 0.6 A
- 2.4 A modules: 0.18 A ... 2.4 A
- 9.0 A modules: 1.5 A ... 9.0 A

5 Summary

The nominal motor current must correspond to the current range of the selected module in order to ensure optimum functionality.

6 Error table

Status	Description	PWR	ERR	L ² /I _{adj}	R ² /ON	Acknowledgment
Message (power path remains connected through)	Message with pending control signal: 2 or more phases are missing No motor connected Motor current in at least 2 phases > 2 s below the minimum current value that can be set Error occurred during reverse running. Error occurred during forward running.	B B	B B	E A	A E	Automatic ^{1/2} Automatic ¹
Explanation: A = LED switched off/E = LED permanently lit/B = LED flashes, approx. 2 Hz (50:50)						

¹ No further action required

² Only for ELR H5-... Devices

7 Product versions from which the function is implemented


Order No.	Designation	New product version	Inventory control since ¹
2900414	ELR H5-IES-SC- 24DC/500AC-2	5	KW31/12
2900420	ELR H5-IES-SC-230AC/500AC-2	4	KW39/12
2900421	ELR H5-IES-SC- 24DC/500AC-9	4	KW30/12
2900422	ELR H5-IES-SC-230AC/500AC-9	3	KW42/12
2900542	ELR H3-I-SC- 24DC/500AC-0,6	4	KW38/12
2900543	ELR H3-I-SC- 24DC/500AC-2	6	KW40/12
2900544	ELR H3-I-SC-230AC/500AC-2	5	KW37/12
2900545	ELR H3-I-SC- 24DC/500AC-9	5	KW39/12
2900546	ELR H3-I-SC-230AC/500AC-9	4	-
2900550	ELR H3-ES-SC- 24DC/500AC-0,6	4	-
2900552	ELR H3-ES-SC- 24DC/500AC-2	5	KW45/12
2900553	ELR H3-ES-SC-230AC/500AC-2	4	KW39/12
2900554	ELR H3-ES-SC- 24DC/500AC-9	4	KW34/12
2900555	ELR H3-ES-SC-230AC/500AC-9	3	-
2900558	ELR H5-ES-SC- 24DC/500AC-0,6	4	-
2900559	ELR H5-ES-SC- 24DC/500AC-2	5	KW41/12
2900560	ELR H5-ES-SC-230AC/500AC-2	4	-
2900561	ELR H5-ES-SC- 24DC/500AC-9	4	KW25/12
2900562	ELR H5-ES-SC-230AC/500AC-9	3	KW34/12
2900566	ELR H3-IES-SC- 24DC/500AC-0.6	4	KW33/12
2900567	ELR H3-IES-SC- 24DC/500AC-2	5	KW34/12
2900568	ELR H3-IES-SC-230AC/500AC-2	4	-

Order No.	Designation	New product version	Inventory control since ¹
2900569	ELR H3-IES-SC- 24DC/500AC-9	4	KW31/12
2900570	ELR H3-IES-SC-230AC/500AC-9	4	KW44/12
2900573	ELR H5-I-SC- 24DC/500AC-0,6	4	KW41/12
2900574	ELR H5-I-SC- 24DC/500AC-2	6	KW38/12
2900575	ELR H5-I-SC-230AC/500AC-2	5	KW40/12
2900576	ELR H5-I-SC- 24DC/500AC-9	5	KW39/12
2900578	ELR H5-I-SC-230AC/500AC-9	4	-
2900582	ELR H5-IES-SC- 24DC/500AC-0.6	4	KW32/12
2900685	ELR H3-I-SC-230AC/500AC-0.6	3	KW34/12
2900686	ELR H3-ES-SC-230AC/500AC-0,6	3	-
2900688	ELR H5-ES-SC-230AC/500AC-0,6	3	-
2900689	ELR H3-IES-SC-230 AC/500 AC-0.6	3	-
2900691	ELR H5-I-SC-230 AC/500 AC-0.6	3	-

¹ See date code

Location of the date code (1) on the module

Format: <week><year>





**SCATTERGOOD
& JOHNSON LTD**
ELECTRICAL ENGINEERING & FLUID CONTROL DISTRIBUTORS

Est.1899

At Scattergood & Johnson Ltd, we pride ourselves on being a technical distributor to specialist industries.

Working with a range of quality product suppliers across a number of specialist markets, we are not your average 'box shifter' - we are your technical and supply chain partner.

We fully support every product we sell - for free! Our internal team and external sales engineers can answer any product or application question, no matter the complexity.

Backing up this technical ability is a range of 50,000+ products available from stock for nationwide next day delivery (same day if required!), or you can collect what you need from any of our trade counters around the UK.

Select your specialist interest below to learn more about how we can help.



Online, In Branch and On the Road - Scattergood & Johnson Ltd, there when you need us.

www.scatts.co.uk