

## Instruction sheet MTL process alarm equipment

October 2016  
INS P861 Rev 4

**CROUSE-HINDS**  
SERIES

# RTK P861

## MTL intrinsically safe LED lamp

### Description

The RTK P861 MTL LED lamp provides visual on/off indication of process conditions in both safe and hazardous areas. Available in a choice of six super-bright colours (red, orange, yellow, green, blue and white), they are ideally suited as part of a panel mounting indicator or illuminated pushbutton assembly.

The P861 itself is a standard BA9s intrinsically safe LED lamp which can be supplied as part of a pilot light or illuminated pushbutton or alternatively supplied separately to be used in any standard switch or lamp assembly. (This assumes that when used in a hazardous area that the special conditions for safe use are adhered to).

With the LED lamp being current limited to take a maximum of only 20mA, it is possible to drive two lamps from a single IIC interface without any affect on the brightness.

With the LED's low power consumption, low heat dissipation and long life expectancy, the P861 is an ideal indicator for safe and hazardous areas alike.

### Installation

The P861 LED lamp can be supplied as a loose item or as an integral part of the RTK DA170 range of illuminated pushbuttons, RTK DFR30IS display facias or RTK DA180 range of giant LED clusters.

In hazardous areas the LED lamps must be powered through suitable intrinsically safe isolators or barriers. Up to two LED lamps can be driven from a single IIC interface.

When supplied loose the LED lamp will need to be fitted to a suitable lamp-holder/enclosure to suit the application bearing in mind the conditions for safe use when using in a hazardous area. In these cases the end terminal of the lamp is the positive and the body of the lamp itself is the negative.

When supplied as part of a DA170 illuminated pushbutton then the P861 lamps are supplied pre-fitted into the integral BA9s lamp holder with terminals marked X1 and X2. To illuminate the lamp, connect X1 to positive and X2 to negative. If these are connected incorrectly the lamp will not illuminate but will not be damaged in any way, simply reverse the two connections.

When supplied as part of a DA180 giant cluster then the P861 lamps are supplied pre-fitted into the integral BA9s lamp holder with terminals marked X1 and X2. To illuminate the lamp, connect X1 to positive and X2 to negative. If these are connected incorrectly the lamp will not illuminate but will not be damaged in any way, simply reverse the two connections.

### Hazardous area use

The LED lamps must be powered through suitable intrinsically safe isolators or barriers. Up to two LED lamps can be driven from a single IIC interface.

The LED lamp must be protected to IP20 minimum once installed.

### Safe area use

A power source of 14-26VDC is applied to the LED lamp in order to illuminate the LED lamp.



**Eaton Electric Limited,**  
Great Marlings, Butterfield, Luton  
Beds, LU2 8DL, UK.  
Tel: + 44 (0)1582 723633 Fax: + 44 (0)1582 422283  
E-mail: rkenquiny@eaton.com  
www.mtl-inst.com

© 2016 Eaton  
All Rights Reserved  
Publication No. INS P861 Rev 4  
October 2016

RTK P861

October 2016

**Specification****HAZARDOUS AREA USE****Certification**

ATEX certified to to EN60079-0:2012 and EN60079-11:2012

Group II, Category 2

⊕ II 2G Ex ia IIC Gb T4 (Ta-20°C to 60°C)

**Location**

Zones 1 and 2, Gas Groups IIC, IIB and IIA, Temp Class up to T4

**Certificate number**

Baseefa14ATEX0007X

**Safety Parameters**

Only for connection to certified intrinsically safe circuits with the following maximum values:

$U_i = 30V$

$P_i = 1.0W$   $I_i = 2A$ ,  $C_i = 0nF$   $L_i = 0mH$

**Supply**

With suitable certified interface 18-35VDC, current 20mA

**Recommended interfaces**

Zener Barriers: MTL7728P+

IS Isolators: MTL5521

**Environment**

Operating temperature: -20°C to +60°C

Storage temperature: -20°C to +80°C

Humidity: 0-95% RH, non-condensing

**Compliance**

Immunity to EN61000-6-2:2005

Emissions to EN6100-6-4:2007

**SAFE AREA USE****Power supply requirements**

Direct connection: 14-26VDC

Current consumption: 20mA maximum per lamp

**Environment**

Operating temperature: -20°C to +60°C

Storage temperature: -20°C to +80°C

Humidity: 0-95% RH, non-condensing

**GENERAL****High Reliability**

All LED lamps are designed to provide a minimum of 100,000 hours service life (continuous illumination at 40°C ambient temperature).

**Colours**

The P861 range of LED lamps are available in six super-bright colours. Colours are red, orange, yellow, green, blue and white.

**WHEN SUPPLIED DA170 ILLUMINATED PUSHBUTTON****Construction**

Housing/mounting collar: Polyamide 6.6/reinforced fibreglass FR4

Lens: Polycarbonate

**Protection**

IP65 when panel mounted, IP20 from the rear

**Mounting**

Lamp- BA9s bulb holder

Pushbutton, Pilot Light – Through 22.5 mm diameter hole

**Connections**

Screw terminals for cable 0.5–2.5 mm<sup>2</sup>

**RTK P861**


October 2016

**BA9s LED lamp**

The P861 LED lamp itself has a standard BA9s fitting and can be used in any suitable pilot light or pushbutton, taking the special conditions for safe use as shown in the certificate into account.

**Connections**

The end terminal of the lamp is the positive and the body of the lamp itself is the negative.

**Special conditions for safe use****1. General**

- 1.1 The terminations of the lamp holder shall be marked as intrinsically safe in accordance with clause 12.2 of EN 60079-11, when also non-intrinsically safe apparatus are installed in the same enclosure (For instance circuits connected to terminals in type of protection increased safety Ex e).
- 1.2 When more than one intrinsically safe circuit is installed in the same enclosure and/or also non intrinsically safe circuits are installed in that same enclosure, the separations between the circuits have to be assured in accordance with EN 60079-11, taking into account a possible addition of the voltage of the circuits.

**2. LED lamp of the P861 range (including fittings).**

- 2.1 When the LED lamp of the P861 range is mounted in a lamp holder containing other circuits, the lamp holder shall be fitted in an enclosure providing ingress protection of at least IP20 in accordance with EN60529.

When a higher ingress protection is required this has to be achieved by an enclosure, which is suitable for the applicable environmental conditions, in accordance with EN 60079-0 and EN 60079-11.

- 2.2 For the illuminated push-button assembly as specified in the test documentation listed at (19), the special conditions for safe use are met when all the circuits connected to it are intrinsically safe, have a maximum peak voltage of 375V and the required ingress protection has been take into account.

This illuminated push-button assembly has an ingress protection of IP20 in accordance with EN 60529. This assembly consists of the following parts (or equivalent): lamp holder DA170-LH, switches DA170-SW on either side of the lamp holder, which are fitted on Body DA170-BD and operated by actuator DA170-AC.

**3. Giant LED cluster of the DA180 range.**

- 3.1 When more than one giant LED cluster of the DA180 range is mounted on an enclosure or the enclosure contains also other circuits, the enclosure shall provide a degree of ingress protection in accordance with EN 60529 suitable for the applicable environmental conditions and comply with EN60079-0 and EN60079-11.

*Due to our policy of continuous product development, we reserve the right to amend these specifications without notice.*

# CROUSE-HINDS

## SERIES

### AUSTRALIA

MTL Instruments Pty Ltd  
10 Kent Road, Mascot,  
New South Wales, 2020, Australia  
Tel: + 61 1300 308 374 Fax: + 61 1300 308 463  
E-mail: mtl-salesanz@eaton.com

### BeNeLux

MTL Instruments BV  
Ambacht 6, 5301 KW Zaltbommel  
The Netherlands  
Tel: +31 (0)418 570290 Fax: +31 (0)418 541044  
E-mail: mtl.benelux@eaton.com

### CHINA

Cooper Electric (Shanghai) Co. Ltd  
955 Shengli Road, Heqing Industrial Park  
Pudong New Area, Shanghai 201201  
Tel: + 86 2128993817 Fax: + 86 2128993992  
E-mail: mtl-cn@eaton.com

### FRANCE

MTL Instruments srl,  
7 rue des Rosières, 69410 Champagne au Mont d'Or  
France  
Tel: + 33 (0) 4 37 46 16 53 Fax: + 33 (0) 4 37 46 17 20  
E-mail: mtfrance@eaton.com

### GERMANY

MTL Instruments GmbH,  
Heinrich-Hartz-Str. 12, 50170 Kerpen, Germany  
Tel: + 49 (0)22 73 98 12-0 Fax: + 49 (0)22 73 98 12-2 00  
E-mail: cskkerpen@eaton.com

### INDIA

MTL India,  
No.36, Nehru Street, Off Old Mahabalipuram Road  
Sholinganallur, Chennai- 600 119, India  
Tel: + 91 (0) 44 24501660 /24501857 Fax: + 91 (0) 44 24501463  
E-mail: mtlindiasales@eaton.com

### ITALY

MTL Italia srl,  
Via San Bovio, 3, 20090 Segrate, Milano, Italy  
Tel: +39 (0)2 959501 Fax: +39 (0)2 95950759  
E-mail: chmninfo@eaton.com

### JAPAN

Cooper Crouse-Hinds Japan KK,  
MT Building 3F 2-7-5 Shiba Daimon, Minato-ku,  
Tokyo, Japan 105-0012  
Tel: + 81 (0)3 6430 3128 Fax: + 81 (0)3 6430 3129  
E-mail: mtl-jp@eaton.com

### NORWAY

Norex AS  
Norex 7c, Postboks 147,  
N-1378 Nesbru, Norway  
Tel: +47 66 77 43 80 Fax: +47 66 84 55 33  
E-mail: info@norex.no

### RUSSIA

Cooper Industries Russia LLC  
Elektrozavodskaya Str 33  
Building 4  
Moscow 107076, Russia  
Tel: +7 (495) 981 3770 Fax: +7 (495) 981 3771  
E-mail: mtrussia@eaton.com

### SINGAPORE

Cooper Crouse-Hinds Pte Ltd  
No 2 Serangoon North Avenue 5, #06-01 Fu Yu Building  
Singapore 554911  
Tel: +65 6 645 9864 / 5 Fax: +65 6 487 7997  
E-mail: sales.mtlsing@eaton.com

### SOUTH KOREA

Cooper Crouse-Hinds Korea  
7F Parkland Building 237-11 Nhyun-dong Gangnam-gu,  
Seoul 135-546, South Korea.  
Tel: +82 6380 4805 Fax: +82 6380 4839  
E-mail: mtl-korea@eaton.com

### UNITED ARAB EMIRATES

Cooper Industries/Eaton Corporation  
Office 205/206, 2nd Floor S.J Towers, off. Old Airport Road,  
Abu Dhabi, United Arab Emirates  
Tel: +971 2 44 66 840 Fax: +971 2 44 66 841  
E-mail: mtgulf@eaton.com

### UNITED KINGDOM

Eaton Electric Ltd,  
Great Marlings, Butterfield, Luton  
Beds LU2 8DL  
Tel: +44 (0)1582 723633 Fax: +44 (0)1582 422283  
E-mail: mtlenquiry@eaton.com

### AMERICAS

Cooper Crouse-Hinds MTL Inc.  
3413 N. Sam Houston Parkway W,  
Suite 200, Houston TX 77066, USA  
Tel: +1 281-571-8065 Fax: +1 281-571-8069  
E-mail: mtl-us-info@eaton.com



**Eaton Electric Limited,**  
Great Marlings, Butterfield, Luton  
Beds, LU2 8DL, UK.  
Tel: + 44 (0)1582 723633 Fax: + 44 (0)1582 422283  
E-mail: rikenquiry@eaton.com  
www.mtl-inst.com  
© 2016 Eaton  
All Rights Reserved  
Publication No. INS P861 Rev 4 121016  
October 2016

**EUROPE (EMEA):**  
+44 (0)1582 723633  
mtlenquiry@eaton.com

**THE AMERICAS:**  
+1 800 835 7075  
mtl-us-info@eaton.com

**ASIA-PACIFIC:**  
+65 6645 9864 / 6645 9865  
sales.mtlsing@eaton.com

The given data is only intended as a product description and should not be regarded as a legal warranty of properties or guarantee. In the interest of further technical developments, we reserve the right to make design changes.



# SCATTERGOOD & JOHNSON LTD

ELECTRICAL ENGINEERING & FLUID CONTROL DISTRIBUTORS

Est.1899

At Scattergood & Johnson Ltd, we pride ourselves on being a technical distributor to specialist industries.

Working with a range of quality product suppliers across a number of specialist markets, we are not your average 'box shifter' - we are your technical and supply chain partner.

We fully support every product we sell - for free! Our internal team and external sales engineers can answer any product or application question, no matter the complexity.

Backing up this technical ability is a range of 50,000+ products available from stock for nationwide next day delivery (same day if required!), or you can collect what you need from any of our trade counters around the UK.

Select your specialist interest below to learn more about how we can help.



Online, In Branch and On the Road - Scattergood & Johnson Ltd, there when you need us.

# [www.scatts.co.uk](http://www.scatts.co.uk)