

# EU-Type Examination Certificate



In accordance with EC NOTICE TO STAKEHOLDERS  
**WITHDRAWAL OF THE UNITED KINGDOM AND EU RULES IN  
 THE FIELD OF INDUSTRIAL PRODUCTS** dated 13 March 2020.

This issued certificate - Certificate No: ITS02ATEX2006X

## 1. EU-TYPE EXAMINATION CERTIFICATE

2. **Equipment or Protective System Intended for use in Potentially Explosive Atmospheres**  
 Directive 2014/34/EU

3. **EU-Type Examination Certificate Number:** ITS02ATEX2006X Issue 1

4. **Product:** BA386 LED Beacon

Name: Fabrizio Massei

5. **Manufacturer:** BEKA associates Ltd

Position: ATEX Certification Officer

6. **Address:** Old Charlton Road  
 Hitchin, Herts SG5 2DA  
 United Kingdom

Date: 18 December 2020

7. This product and any acceptable variation hereto is specified in the schedule to this certificate and the documents therein referred to.

8. Intertek Testing and Certification Limited, Notified Body number 0359 in accordance with Article 17 of Directive 2014/34/EU of the European Parliament and of the Council dated 26 February 2014, certifies that the product has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of products intended for use in potentially explosive atmospheres given in Annex II to the Directive.

In accordance with Article 41 of Directive 2014/34/EU, EC-Type Examination Certificate referring to 94/9/EC that were in existence prior to the date of application of 2014/34/EU (20 April 2016) may be referenced as if they were issued in accordance with Directive 2014/34/EU. New issues of such EC-Type Examination Certificates, and Supplementary Certificates to such certificates, may continue to bear the original certificate number issued prior to 20 April 2016.

The examination and test results are recorded in confidential Intertek Report Ref 01006218, dated March 2002 and Intertek Report Ref 103015675LHD-001 Issue 1 dated December 2017.

9. Compliance with the Essential Health and Safety Requirements has been assured by compliance with EN 60079-0:2012 + A11:2013, EN 60079-11:2012 and EN 60079-28:2015 except in respect of those requirements referred to at item 16 of the Schedule.

10. If the sign "X" is placed after the certificate number, it indicates that the product is subject to Specific Conditions of Safe Use specified in the Schedule to this certificate.

11. This EU-Type Examination Certificate relates only to the design and construction of the specified product. Further requirements of the Directive apply to the manufacturing process and supply of this product. These are not covered by this certificate.

12. The marking of the product shall include the following:



II 1 G Ex ia op is IIC T4 Ga  
 $-40^{\circ}\text{C} \leq T_a \leq +60^{\circ}\text{C}$

**Intertek Testing & Certification Limited**  
 Intertek House, Cleeve Road, Leatherhead, Surrey, KT22 7SA  
 Tel: +44 (0)1372 370900 Fax: +44 (0)1372 370977  
[www.intertek.com](http://www.intertek.com)

Registered No 3272281 Registered Office: Academy Place, 1-9 Brook Street, Brentwood, Essex, CM14 5NQ.

**V K Varma**  
 Certification Officer  
 19 December 2017

# EU-Type Examination Certificate


**Intertek**

Valued Quality. Delivered.

## SCHEDULE

### EU-TYPE EXAMINATION CERTIFICATE NUMBER ITS02ATEX2006X Issue 1

#### 13. Description of Equipment or Protective System

The BEKA BA386 LED Beacon is designed to produce a visual warning in the hazardous area. The BA386 may come in red, green, amber, blue, white or special colour models. The equipment includes a three printed circuit boards housed within a two-parts plastic enclosure, a translucent lens and a back box. The enclosure provides a degree of protection of at least IP20. Intrinsic safety is assured by limitation of voltage, current and power, limitation of capacitance and infallible segregation.

The BA386 LED Beacon may alternatively be identified as an LI 01 L-IS-C LED Beacon.

The maximum intrinsically safe input parameters are as follows:

Power supply PL2 terminals 1 and 2:

$U_i = 28V$  dc

$I_i = 110mA$  dc

$P_i = 0.8W$

The equivalent parameters are:

$C_i = 0$

$L_i = 0$

Optional Sounder PL2 terminals 3 and 4

$U_o = 28V$  dc

$I_o = 110mA$  dc

$P_o = 0.8W$

The equivalent parameters are:

$C_i = 0$

$L_i = 0$

Optional Alarm Accept Switch PL 1 terminals 5 and 6

$U_o = 16.8V$  dc

$I_o = 1.6mA$  dc

$P_o = 7.0mW$

The equivalent parameters are:

$C_i = 0$

$L_i = 0$

#### 14. Report Number

Intertek Report Ref 01006218, dated March 2002

Intertek Report Ref 103015675LHD-001 Issue 1 dated December 2017

#### 15. Special Conditions of Certification

##### (a). Specific Conditions of Safe Use

- The equipment includes exposed unearthed metal label. Metallic label can present capacitance of up to 6pF with reference to earth. It is the responsibility of the user to determine the suitability of the equipment for its intended application.
- When installed in potentially explosive atmosphere requiring apparatus of Category 1G, the equipment shall be installed such that even in the event of rare incidents, an ignition source due to impact or friction between aluminium label and other iron/steel parts is excluded.

##### (b). Conditions of Manufacture - Routine Tests

- None.





# SCATTERGOOD & JOHNSON LTD

ELECTRICAL ENGINEERING & FLUID CONTROL DISTRIBUTORS

Est.1899

At Scattergood & Johnson Ltd, we pride ourselves on being a technical distributor to specialist industries.

Working with a range of quality product manufacturers across a number of specialist markets, we are not your average 'box shifter' - we are your technical and supply chain partner.

We fully support every product we sell - for free! Our internal team and external sales engineers can answer any product or application question, no matter the complexity.

Backing up this technical ability is a range of 50,000+ products available from stock for nationwide next day delivery (same day if required!), or you can collect what you need from any of our trade counters around the UK.

Select your specialist interest below to learn more about how we can help.



Online, In Branch and On the Road - Scattergood & Johnson Ltd, there when you need us.

# [www.scatts.co.uk](http://www.scatts.co.uk)