



R88M-1M7K515C-S2

1S AC servo motor, 7.5 kW, 400 VAC, 1500 rpm, 47.8 Nm, absolute encoder

Specifications

Servo control method	EtherCAT
Drive supply voltage	400 V three phase
Rated output	7.5 kW
Rated speed	1500 r/min
Rated torque	47.8 Nm
Peak torque	119 Nm
Encoder type	Absolute without battery
Encoder resolution	23 Bit
Motor with brake	✘
Motor with oil seal	✘
Flange size square (LC)	180 mm
Shaft diameter	42 mm
Shaft with key	✔
Shaft with tap	✔
Product Weight (unpacked)	39000 g



R88D-1SN75F-ECT

1S servo drive, EtherCAT
type, 7.5 kW, 3~ 400 VAC



R88A-CA1H005SF

1S series servo motor power cable, 5 m, non braked, 400 V: 7.5 kW



R88A-CA1H010SF

1S series servo motor power cable, 10 m, non braked, 400 V: 7.5 kW



R88A-CR1B001-5NF-E

1S series servo encoder cable, 1.5m, 230V: 900W-1.5kW, 400V: 400W-15kW



R88A-CR1B003NF-E

1S series servo encoder cable, 3m, 230V: 900W-1.5kW, 400V: 400W-15kW



R88A-CR1B005NF-E

1S series servo encoder cable, 5m, 230V: 900W-1.5kW, 400V: 400W-15kW



R88A-CR1B010NF-E

1S series servo encoder cable, 10m, 230V: 900W-1.5kW, 400V: 400W-15kW



R88A-CR1B015NF-E

1S series servo encoder cable, 15m, 230V: 900W-1.5kW, 400V: 400W-15kW



R88A-CR1B020NF-E

1S series servo encoder cable, 20m, 230V: 900W-1.5kW, 400V: 400W-15kW

CAD Library



1S Series Users Manual

EN PDF 22.5 MB



1S Series - Expanded with high capacity range: 4 - 15 kW Flyer

EN PDF 1.64 MB



1S Series Incremental Encoder Type Users Manual

EN PDF 6.34 MB



1S Series Multi-axis Setup and Tuning Getting Started Guide

EN PDF 7.86 MB



1S Servo System Brochure

EN PDF 25.2 MB



1S-series Servos Instruction Manual

EN PDF 5.63 MB



AC Servomotor_Servo Drives - Replace Guide Replacement guide

EN PDF 4.74 MB



EAC Mark removal Discontinuation Notice

EN PDF 221 KB



Motor Sizing Tool Operation Manual

EN PDF 3.83 MB



R88M-1_1S-series Servo Motor Datasheet

EN PDF 1.56 MB



Redundancy and Motion Safety Flyer

EN PDF 960 KB



Sysmac Catalogue

EN PDF 43.5 MB



Sysmac: A Fully Integrated Platform Brochure

EN PDF 11.8 MB



Using R88A-CA1G power cables Technical Information

EN PDF 1.6 MB



motor_sizing_tool_v1.80.1.16 Configurator

EN ZIP 36.1 MB